

SWITCHMODE BATTERY CHARGERS

Model BCS-WSC-1230SB

12 Volt 30 Amp (With 2 Amp Output) Fully Automatic SwitchMode Battery Charger



- Premium Switchmode Battery Charger, Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances,
- Solar, Deep Cycle, UPS Standby
- Battery types: Lead-acid/GEL/AGM/LiFePO4

Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue

Castle Hill NSW 2154 Australia

Features

Microprocessor controller inside
Full range AC input
Power factor correction > 0.97
High efficiency
4 Stages charging I-Uo-U-Equalization
Battery charger and power supply selectable
Compact and light weight
Maintains batteries in perfect condition and prolong their useful life

Performance, Physical and Dimensional Properties

Input voltage range: 100 - 240VAC
Input frequency: 50 - 60Hz
Power factor correction: >0.97
Efficiency at 230VAC: >91%
Efficiency at 115VAC: >88%
Input current at 230VAC: 2.2A
Input current at 115VAC: 4.2A
Charge mode: Normal 3-Stage / Equalization 4-Stage
Output charging voltage: 14V / 14.4V / 14.8V
Output float voltage: 13.5V / 13.8V
Output power mode voltage: 13.2V
Output charging current: 0 - 30A
Equalization mode: 14.8V / 15.5V (0 - 8A)
Half power mode (Silent mode): 0 - 15A
Battery connection: 2
Battery capacity: 300Ah
SB charging voltage: 13.8V
SB charging current: 2A
SB connection (Starter battery): 1
Operating temperature: -20°C ~ +50°C
Dimension (L x W x H): 265 x 171 x 70 mm
Weight: 1.6 kgs
Option: Remote control RC-600
Option: Temperature compensation TF-100

Protection

Short circuit protection, Over voltage protection, over current protection, over temperature protection