

BCS SWITCHMODE BATTERY CHARGERS

Model BCS-WSC-2425

24 Volt 25 Amp Fully Automatic SwitchMode Battery Charger



- Premium Switchmode Battery Charger, Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances,
- Solar, Deep Cycle, UPS Standby
- Battery types: Lead-acid/GEL/AGM/LiFePO4

Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue

Castle Hill NSW 2154 Australia

Features

Microprocessor controller inside

Full range AC input

Power factor correction > 0.97

High efficiency

4 Stages charging I-Uo-U-Equalization

Battery charger and power supply selectable

Compact and light weight

Maintains batteries in perfect condition and prolong their useful life

Performance, Physical and Dimensional Properties

Input voltage range: 100-240VAC

Input frequency: 50-60Hz

Power factor correction: >0.97

Efficiency at 230VAC: >93%

Efficiency at 115VAC: >91%

Input current at 230VAC: 3.51A

Input current at 115VAC: 7.1A

Charge mode: Normal 3-Stage/Equalization 4-Stage

Output charging voltage: 28V/28.8V/29.6V,

Output float voltage: 27V/27.6V

Output power mode voltage: 26.4V

Output charge current: 0-25A

Equalization mode: 29.6V/31V (0-12.5A)

Half power mode (Silent mode): 0-12.5A

Battery connection: 3

Battery capacity: 250Ah

Operating temperature: -20°C ~ +50°C

Dimension (L x W x H): 292 x 210 x 75 mm

Weight: 2.5 kgs

Option: Remote control RC-600 or RC-601D

Option: Temperature compensation TF-100

Protection

Short circuit protection, Over voltage protection, over current protection, over temperature protection